
3. Installation

3-1 Installing and Removing the Battery

To install

1. Insert the battery into the opening on the back of the phone making sure the plastic tab on the back is inserted into the matching slot in the phone.
2. Press up until the latch snaps into place.

To remove

1. So that no stored messages or numbers are lost, power off your phone by pressing and holding the [PWR] key.
2. Push the battery release latch up completely. The battery will separate slightly from the phone.
3. Slide the battery down and remove.

3-2 For Desk Top Use

1. Choose a proper location to install the charger for desk top use.
2. Plug the power cord of the charger into an appropriate wall socket. When the power is connected correctly, the lamps turn on briefly.
3. To charge the battery pack, insert the pack into the rear slot of the charger. The lamp on the front panel of the charger lights up red.
4. If you do not wish to use the phone while charging the battery, insert the phone with the battery pack attached into the front slot of the charger. The lamp on the front panel of the charger lights up red.

Specifications using DTH (Desk Top Charger)

Battery Type	Standard Battery (Li-ion, 1000mAh)
Charging Time	2 hours
SEC Code	GH43-01025A